

## AUDIO Music 81

### Tragbares Radio mit RDS Funktionalität und hervorragendem Klang

- Dieses Radio ist konzipiert für Leute die Wert auf eine einfache Bedienung und einen guten Klang legen.
- Der Synthesizer Tuner mit UKW, MW, LW, KW und seinen 40 Senderspeichern vereinfacht die Speicherung und Anwahl Ihrer Lieblingssender.
- Dank RDS wird Ihnen der Sendername und die Uhrzeit automatisch in dem großen, beleuchtbaren Display angezeigt.
- Durch die einfache Bedienung verbunden mit den ausgezeichneten Empfangsqualitäten ist dieses Radio ideal für zuhause oder Unterwegs.
- Der eingebaute, hochwertige Lautsprecher sorgt für einen hervorragenden Klang.

### Portable radio with RDS comfort and excellent sound

- This Radio is designed for people who evaluate to place onto simple operation and good sound quality.
- The PLL tuner with FM, AM, LW, SW and 40 station presets makes it simple to use and save your favorite stations.
- With RDS you get the station name and the automatic clock time on the big illuminated display.
- The simple operation in combination with the excellent reception characteristics of this radio make it ideal for use at home or in your free time.
- The built in high-end loudspeaker provides a very good sound quality.



**GRR2600**  
Ean: 4013833623977



**GRR2610**  
Ean: 4013833873914

# Music 81

## Verstärkerteil

1,5/1,2 Watt Musik-/Sinusleistung, Klangregler für individuelle Klangeinstellung, Automatische Loudness

## Tunerteil

Wellenbereiche, UKW, MW, LW, KW, PLL - Frequenz - Synthesizer - Abstimmung, Radio Daten System RDS, RDS -Radiotext, Local/DX-Schalter, Autom. und manueller Sendersuchlauf, Senderspeicher: 10 FM, 10 MW, 10 LW, 10 SW, Last Station Memory, Teleskop- und Ferritantenne, Automatischer Sendersuchlauf mit Speicherung empfangsstarker Sender (ATS) bei FM

## Stromversorgung

Batterien: 4 x 1.5 V (LR20, AM1, D)  
 Netzteil: 230 V~, Netzfrequenz: 50Hz/ 60Hz

## Uhr

Wochentag-Anzeige, RDS-Uhrzeit-Anzeige, Einschlafzeit-Automatik bis zu 90 Min. programmierbar, Wecken mit Musik oder Alarmsignal, Nachwecken in 5-Min-Abständen möglich

## Display

kurzzeit beleuchtet, LC-Display

## Gehäuse (BxHxT, mm)

300 x 160 x 100

## Gewicht

1,22 kg

## Lautsprecher

1x 100mm Breitband

## Anschlüsse

Kopfhörer, Netz: 230V 50/60 Hz

## Lieferumfang

Garantie-Hinweis, Netzkabel, Bedienungsanleitung

## Farbe

Schwarz, weiss

## Amplifier Part

1,5/1,2 watts music/nominal power, Tone control for individual sound adjustment, Automatic loudness control

## Tuner Part

Wave bands, FM, AM, LW, SW, PLL frequency synthesizer tuning, Radio Data System RDS, RDS radio text, Local/DX switch, Automatic and manual station search, Station presets: 10 FM, 10 AM, 10 LW, 10 SW, Last station memory, Telescopic and ferrite antenna, Automatic tuning search and storage of station with strong reception strength for FM

## Power Supply

Batteries: 4 x 1.5 V (LR20, AM1, D)  
 Mains supply: 230 V~, Mains frequency: 50Hz/ 60Hz

## Clock

Weekday indication, RDS time signal, Sleep function, programmable up to 90 minutes, Alarm by radio or by buzzer signal, 5-minute-interval repeat alarm facility (snooze)

## Display

short time illuminated, LC display

## Cabinet (WxHxD, mm)

300 x 160 x 100

## Net weight

1,22 kg

## Loudspeaker

1x 100mm wide range

## Connection

Headphone, Mains: 230V 50/60 Hz

## Included in delivery

Warranty sheet, mains cable, instruction booklet

## Color

Black, white